## Operational Amplifiers, Dual Power, 1.0 A Output Current

## TCA0372, TCA0372B, NCV0372B

The TCA0372 is a monolithic circuit intended for use as a power operational amplifier in a wide range of applications, including servo amplifiers and power supplies. No deadband crossover distortion provides better performance for driving coils.

#### Features

- Output Current to 1.0 A
- Slew Rate of 1.3 V/µs
- Wide Bandwidth of 1.1 MHz
- Internal Thermal Shutdown
- Single or Split Supply Operation
- Excellent Gain and Phase Margins
- Common Mode Input Includes Ground
- Zero Deadband Crossover Distortion
- NCV devices are AEC-Q100 Qualified and PPAP Capable
- These Devices are Pb–Free, Halogen Free/BFR Free and are RoHS Compliant



Figure 1. Representative Block Diagram



#### **ON Semiconductor®**

#### www.onsemi.com



#### MARKING DIAGRAMS



= Pb-Free Package

G

#### **PIN CONNECTIONS**



#### **ORDERING INFORMATION**

See detailed ordering and shipping information in the package dimensions section on page 5 of this data sheet.

#### **MAXIMUM RATINGS**

Rating	Symbol	Value	Unit
Supply Voltage (from $V_{CC}$ to $V_{EE}$ )	V <sub>S</sub>	40	V
Input Differential Voltage Range	V <sub>IDR</sub>	Note 1	V
Input Voltage Range	V <sub>IR</sub>	Note 1	V
Junction Temperature (Note 2)	Т <sub>Ј</sub>	+150	°C
Operating Temperature Range	T <sub>A</sub>	-40 to +125	°C
Storage Temperature Range	T <sub>stg</sub>	–55 to +150	°C
DC Output Current	۱ <sub>۵</sub>	1.0	А
Peak Output Current (Nonrepetitive)	I <sub>(max)</sub>	1.5	A
Thermal Resistance, Junction-to-Air	$R_{ ext{ heta}JA}$	80	°C/W
Thermal Resistance, Junction-to-Case	$R_{ ext{ heta}JC}$	12	°C/W

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Either or both input voltages should not exceed the magnitude of  $V_{CC}$  or  $V_{EE}$ . 2. Power dissipation must be considered to ensure maximum junction temperature (T<sub>J</sub>) is not exceeded.

	Characteristics	Symbol	Min	Тур	Max	Unit
Input Offset Voltage ( $V_{CM} = T_A = +25^{\circ}C$ T <sub>A</sub> , T <sub>low</sub> to T <sub>high</sub>	0)	V <sub>IO</sub>		1.0 _	15 20	mV
Average Temperature Coeff	cient of Offset Voltage	$\Delta V_{IO} / \Delta T$	-	20	-	μV/°C
Input Bias Current (V <sub>CM</sub> = 0	)	I <sub>IB</sub>	-	100	500	nA
Input Offset Current (V <sub>CM</sub> =	0)	I <sub>IO</sub>	-	10	50	nA
Large Signal Voltage Gain $V_0 = \pm 10$ V, $R_L = 2.0$ k		A <sub>VOL</sub>	30	100	-	V/mV
Output Voltage Swing ( $I_L = T_A = +25^{\circ}C$ $T_A = T_{low}$ to $T_{high}$ $T_A = +25^{\circ}C$ $T_A = T_{low}$ to $T_{high}$	100 mA)	V <sub>OH</sub> V <sub>OL</sub>	14.0 13.9 - -	14.2 _ _14.2 _	- - -14.0 -13.9	V
$\begin{array}{l} Output Voltage Swing (I_L = $$$ $$ $$ $$ $$ $$ $$ $$ $$ $$ $$ $$ $	$T_A = +25^{\circ}C$ $T_A = T_{low}$ to $T_{high}$ $T_A = +25^{\circ}C$	V <sub>OH</sub> V <sub>OL</sub>	22.5 22.5 - -	22.7 - 1.3 -	- - 1.5 1.6	V
Input Common Mode Voltag $T_A = +25^{\circ}C$ $T_A = T_{low}$ to $T_{high}$	e Range	V <sub>ICR</sub>	V <sub>EE</sub> to (V <sub>CC</sub> -1.0) V <sub>EE</sub> to (V <sub>CC</sub> -1.3)		V	
Common Mode Rejection R	atio (R <sub>S</sub> = 10 k)	CMRR	70	90	-	dB
Power Supply Rejection Rat	io (R <sub>S</sub> = 100 Ω)	PSRR	70	90	-	dB
$T_{A} = T_{low}$ to $T_{high}$ TC	A0372 A0372B/NCV0372B A0372 A0372B/NCV0372B	Ι <sub>D</sub>	- - -	5.0 8.0 -	10 10 14 14	mA

#### DC ELECTRICAL CHARACTERISTICS (V<sub>CC</sub> = +15 V, V<sub>EE</sub> = -15 V, R<sub>L</sub> connected to ground, $T_A$ = -40° to +125°C.)

AC ELECTRICAL CHARACTERISTICS ( $V_{CC}$  = +15 V,  $V_{EE}$  = -15 V,  $R_L$  connected to ground,  $T_A$  = +25°C, unless otherwise noted.)

					,
Characteristics	Symbol	Min	Тур	Max	Unit
Slew Rate (V <sub>in</sub> = –10 V to +10 V, R <sub>L</sub> = 2.0 k, C <sub>L</sub> = 100 pF) $A_V$ = –1.0, T <sub>A</sub> = T <sub>low</sub> to T <sub>high</sub>	SR	1.0	1.4	-	V/μs
Gain Bandwidth Product (f = 100 kHz, C <sub>L</sub> = 100 pF, R <sub>L</sub> = 2.0 k) T <sub>A</sub> = 25°C T <sub>A</sub> = T <sub>low</sub> to T <sub>high</sub>	GBW	0.9 0.7	1.4 -	-	MHz
Phase Margin $T_J = T_{low}$ to $T_{high}$ $R_L = 2.0 \text{ k}, C_L = 100 \text{ pF}$	φ <sub>m</sub>	-	65	-	Degrees
Gain Margin $R_L = 2.0 \text{ k}, C_L = 100 \text{ pF}$	A <sub>m</sub>	-	15	-	dB
Equivalent Input Noise Voltage $R_S = 100 \ \Omega$ , f = 1.0 to 100 kHz	e <sub>n</sub>	-	22	-	nV/√Hz
Total Harmonic Distortion $A_V = -1.0$ , $R_L = 50 \Omega$ , $V_O = 0.5$ VRMS, f = 1.0 kHz	THD	-	0.02	-	%

NOTE: In case V<sub>EE</sub> is disconnected before V<sub>CC</sub>, a diode between V<sub>EE</sub> and Ground is recommended to avoid damaging the device.





Figure 8. Sine Wave Response



#### Figure 9. Bidirectional DC Motor Control with Microprocessor-Compatible Inputs



For circuit stability, ensure that  $R_x > \frac{2R3 \cdot R1}{R_M}$  where,  $R_M$  = internal resistance of motor. The voltage available at the terminals of the motor is:  $V_M = 2(V_1 - \frac{V_S}{2}) + |R_0| \cdot I_M$  where,  $|R_0| = \frac{2R3 \cdot R1}{R_X}$  and  $I_M$  is the motor current.

#### Figure 10. Bidirectional Speed Control of DC Motors

#### **ORDERING INFORMATION**

Device	Package	Shipping <sup>†</sup>
TCA0372DWR2G	SOIC-16W (Pb-Free)	1000 / Tape & Reel
TCA0372BDWR2G	SOIC-16W (Pb-Free)	1000 / Tape & Reel
NCV0372BDWR2G*	SOIC-16W (Pb-Free)	1000 / Tape & Reel

+For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

\*AEC-Q100 Qualified and PPAP Capable

#### **MECHANICAL CASE OUTLINE** PACKAGE DIMENSIONS

#### SOIC-16 WB CASE 751G ISSUE E SCALE 1:1 NOTES A DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994. 1. CONTROLLING DIMENSION: MILLIMETERS 2. 16 🗢 0.25@ B@ В DIMENSION & DOES NOT INCLUDE DAMBAR PROTRUSION. з. <u>A A A A</u> RRRR ALLOWABLE PROTRUSION SHALL BE 0.13 TOTAL IN EXCESS OF B DIMENSION AT MAXIMUM MATERIAL CONDITION. DIMENSIONS D AND E DO NOT INCLUDE MOLD PROTRUSIONS. 4. MAXIMUM MOLD PROTRUSION OR FLASH TO BE 0.15 PER SIDE. 5. MILLIMETERS DIM MIN. MAX. H Н Α 2.35 2.65 h 8 45 0.25 A1 0.10 -16X B e DETAIL A в 0.35 0.49 0.2500 TAS BS END VIEW С 0.23 0.32 TOP VIEW D 10.15 10.45 7.40 7.60 Ε 1.27 BSC e 16X н 10.05 10.55 -L h 0.53 REF SEATIN **A1** 0.50 0.90 L SIDE VIEW М 0\* 7\* DETAIL A 2X SCALE 0000|0000 GENERIC 11.00 **MARKING DIAGRAM\*** 1 16X 1.62 .27 XXXXXXXXXXXX PITCH XXXXXXXXXXXX RECOMMENDED AWLYYWWG MOUNTING FOOTPRINT H H Η 1 H Н XXXXX = Specific Device Code = Assembly Location А = Wafer Lot WL YY = Year ww = Work Week G = Pb-Free Package \*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "•", may

DOCUMENT NUMBER:	98ASB42567B	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.			
DESCRIPTION:	SOIC-16 WB		PAGE 1 OF 1		
onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. onsemi does not convey any license under its patent rights nor the rights of others.					

or may not be present. Some products may

not follow the Generic Marking.

# DUSEM

DATE 08 OCT 2021

onsemi, ONSEMI, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "onsemi" or its affiliates and/or subsidiaries in the United States and/or other countries. onsemi owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of onsemi's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent\_Marking.pdf</u>. onsemi reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and onsemi makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does onsemi assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or indental damages. Buyer is responsible for its products and applications using onsemi products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by onsemi. "Typical" parameters which may be provided in onsemi data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. onsemi does not convey any license under any of its intellectual property rights nor the rights of others. onsemi products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification. Buyer shall indemnify and hold onsemi and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs,

#### ADDITIONAL INFORMATION

TECHNICAL PUBLICATIONS:

Technical Library: www.onsemi.com/design/resources/technical-documentation onsemi Website: www.onsemi.com

ONLINE SUPPORT: <u>www.onsemi.com/support</u> For additional information, please contact your local Sales Representative at <u>www.onsemi.com/support/sales</u>